



Description:

The Lamp Proving Module is used to monitor the current flowing in a DC signalling lamp circuit. It provides an output which is OFF when the current is below a pre-set threshold level for more than 0.2 seconds.

The pre-set switching threshold is factory set for 250mAdc

Specifications:

- Mounting: DIN Rail NS32 or NS35/7.5
- Termination: Phoenix Contact 6 way screw terminal
- Power Supply Range: 18 – 30Vdc

Connections:

Terminal 1- Positive Supply 24Vdc (nominal)

Terminal 2- Negative Supply 24Vdc (nominal)

Terminal 3- not used

Terminal 4- not used

Terminal 5- Switched Positive Output (24V nominal)

Terminal 6- Switched Negative Output (24V nominal)

Part Number

The part number is **4212-1000**

e: sales@ar-tech.com.au

p: +61 2 9482 5710

w: ar-tech.com.au

XP4212 r1

